

KAPA Energie

Q600PRO

Pure Sine Wave Inverter



PORTABLE POWER STATION

All-in-One Solar Energy Storage System

Portable Power Station

Outdoor Use

Q600PRO



PHONE CHARGER
10 Wh
35 CHARGES



LED LIGHT
10W
40 HOURS



WIFI ROUTER
10W
40 HOURS



LAPTOP CHARGER
63Wh
6 CHARGE



TELEVISION
50W
8 HOURS



REFRIGERATOR
50W
8 HOURS

Power




600W

Inverter



**Pure
Sine Wave**

Appliances



**No Heating
Appliances**

SPECIFICATIONS

Rated Capacity	409Wh
Inverter	Pure sine wave
DC Output	USB-A(5V/2.4A)x2 USB-C(5V/3A)x1
AC Output	230V,600W output power,1200W surge power x1
Car Port	N/A
DC Input	DC(8mm) 12-30V, 3.5A Max.
Solar Charge	MC4 to 8mm DC adapter, 12-30V
AC Input Port	N/A
LCD	Yes
Size	300.7 mm x 210 mm x 202.7 mm
Weight	6.9kg
Standard accessories	DC charging cord + user manual + MC4 to 8mm adapter

CALCULATION

Power Station Wattage ÷ Appliance Wattage = Hours of Continuous Use

Appliance usage calculations are based off single appliance usage on power stations. Combining appliances will reduce the duration of usage of the power station.

All-in-one Solar Energy System.